

USA Ground Operations CIL Sheet

Critical Item: Circuit Breaker  
 NASA Part No: None  
 Mfg/Part No: Westinghouse / Type BAB  
 System: 60 Hertz Low Voltage Power System

Criticality Category: 1S  
 Total Quantity: 4

Find No.	Qty	Area	PMN	Baseline	Drawing / Sheet
Panel P-42/ CB-18	1	Pad-B	K61-1663	353.25	39K6150023 / 20
Panel P-42/ CB-20	1	Pad-B	K61-1663	353.25	39K6150023 / 20
Panel P-42/ CB-40	1	Pad-B	K61-1663	353.25	39K6150023 / 20
Panel P-42/ CB-41	1	Pad-B	K61-1663	353.25	39K6150023 / 20

**Function:**

Provides circuit overload protection for HVDS racks. Each circuit breaker supplies power to one Hypergol Vapor Detection System equipment rack.

Failure Mode No. Failure Mode	Failure Cause Failure Effect	Detection Method Time to Effect	Crit Cat
09ELB2-001.021 Premature Trip	Internal piece part structural failure  Loss of 60 Hertz Power to associated equipment rack. Loss of Hypergol vapor detection capability at the associated location. Failure could allow loss of life and vehicle during hazardous conditions.	LPS console operator will receive alarm indicating HVDS sensor failure  Immediate	1S

**ACCEPTANCE RATIONALE**

**Design:**

- CB-18/20 Rated: 600V/50 Amp, 3P Estimated Load: 1 Amp Trip Set: 20 Amp
- CB-40/41 Rated: 600V/50 Amp, 3P Estimated Load: 1 Amp Trip Set: 30 Amp
- Environment is normal for application.
- Circuit breaker is used throughout industry.

**Test:**

- OMRSD File VI requires Time/Current trip tests and insulation resistance test performed prior to installation and after a fault per NETA-MTS.

**Inspection:**

- OMRSD File VI requires inspection and maintenance prior to installation and after a fault per NETA-MTS.

**Failure History:**

- Current data on test failures, unexplained anomalies, and other failures experienced during ground processing activities can be found in the PRACA database. The PRACA database was researched and no data was found on this component in the critical failure mode.

**Operational Use:**

Correcting Action	Timeframe
There is no action which can be taken to mitigate the failure effect.	Since no correcting action is available, timeframe does not apply.