

April 19, 1996

CRITICAL ITEMS LIST

PAGE 1

- 1) CIL ITEM : F200-BD-D2
- 2) FMEA CODE : F200-BD
- 3) COMPONENT : SPARK IGNITER CONTROL
- 4) PART NUMBER : DE1493
- 5) SYSTEM/SUBSYSTEM : CONTROLLER/F200-YK
- 6) FAILURE MODE : FAILURE TO ENERGIZE OR MAINTAIN IGNITERS ENERGIZED

- 7) PREPARED : SSME RELIABILITY
- 8) APPROVED :
- 9) DATE : 04-19-96
- 10) REVISION/CHANGE : -001/0
- 11) EFFECTIVITY : -05
- 12) HAZARD REFERENCE: SEE LISTINGS BELOW
- 13) CCDB #

ME3-01-3285

PHASE	FAILURE DESCRIPTION/EFFECT	CRITICALITY
S 4-2	<p>FAILURE OF BOTH IGNITER CHANNELS TO ENERGIZE (IGNITERS OR MAINTAIN IGNITERS ENERGIZED RESULTS IN NO ENGINE IGNITION AND A MCF AND SLE INDICATION. MISSION SCRUB. LOSS OF VEHICLE DUE TO LOX-RICH OPERATION OR LOK DUCT FAILURE MAY RESULT IF FAILURE TO ESTABLISH FPH OR MCC IGNITION OCCURS AND IS NOT DETECTED.</p> <p>REDUNDANCY SCREENS: CONTROLLER SYSTEM: LIKE REDUNDANCY</p> <p>A: PASS. REDUNDANT HARDWARE ITEMS ARE CAPABLE OF CHECKOUT DURING NORMAL GROUND TURNAROUND. B: PASS. LOSS OF A REDUNDANT HARDWARE ITEM IS DETECTABLE DURING FLIGHT. C: PASS. LOSS OF REDUNDANT HARDWARE ITEMS COULD NOT RESULT FROM A SINGLE CREDIBLE EVENT.</p>	<p>IR HAZARD REF: ME-D65, ME-CIS</p>

F-119

CIL ITEM: F200-80-02

DESIGN

DOCUMENT REF.

ALL CAUSES: OUTPUT ELECTRONICS: SPARK IGNITER COMMAND DRIVEN POWER SUPPLY ELECTRONICS: +26 VDC REGULATOR (1)

(1) HONEYWELL BLOCK II
FMEA VOL V OE-F23

THE IGNITERS ARE REDUNDANT ELEMENT PAIRS (1). A FAILURE IN BOTH CONTROLLER CHANNELS (MULTIPLE FAILURE), RESULTING IN LOSS OF FUNCTION, RESULTS IN A CONTROLLER INITIATED SHUTDOWN (2). THE CONTROLLER (WITH SOFTWARE) IS CONFIGURED TO DETECT AND RESPOND PROPERLY TO OUT OF QUALIFICATION LIMIT FAILURES, IMPLEMENT THE APPROPRIATE REDUNDANCY MANAGEMENT RESPONSE, AND COMMAND A SAFE ENGINE STATE WHEN CONTROLLER REDUNDANCY IS LOST (2). HOWEVER, THE CONTROLLER (WITH SOFTWARE) IS NOT CAPABLE OF DETECTING OR RESPONDING TO A FAILURE WHICH RESULTS IN THE LIMITS BEING MONITORED FAILING WITHIN ENGINE REDLINE LIMITS OR WITHIN NORMAL ENGINE OPERATING CONDITIONS (2).

(1) DSHG8977A1
(2) CP406R0008
3.1.3:4
3.2.1:6.3
3.2.3:2.3
3.2.3:3
3.2.3:6
3.2.4

ELECTRICAL, MECHANICAL, AND ELECTROMECHANICAL PARTS FOR THE CIRCUITS INVOLVED IN THIS FUNCTION HAVE BEEN SELECTED FROM THE CLASS S OR EQUIVALENT APPROVED PARTS SELECTION LIST (1), QUALITY ASSURANCE AND SCREENING REQUIREMENTS FOR HIGH RELIABILITY MICROCIRCUITS (2), AND THE SPECIFICATION CONTROL DRAWING FOR MICROCIRCUITS, MONOLITHIC SILICON, AND TRANSISTOR-TRANSISTOR LOGIC (TTL) FAMILY OF DEVICES (3). PRIOR TO INSTALLATION ON THE CARD ASSEMBLIES, COMPONENTS ARE SUBJECTED TO A BURN-IN PERIOD WHERE PARTS ARE ENERGISED AT TEMPERATURES IN EXCESS OF NORMAL CONTROLLER OPERATING ENVIRONMENT, BUT LESS THAN COMPONENT MAXIMUM SPECIFIED OPERATING ENVIRONMENT, TO SCREEN FOR INFANT MORTALITY (4). IN ADDITION TO THESE REQUIREMENTS, ALL COMPONENTS ARE DERATED FROM THE MAXIMUM RATING AT OPERATING EXTREMES (5). CLEANLINESS AND ALL PROCESSES USED DURING MANUFACTURE ARE CONTROLLED BY SPECIFICATION REQUIREMENTS (5).

(1) 85M03928,
85M03929
(2) 85M02704
(3) 85M03766
(4) 85M03876
(5) DSHG8977A1

THE CONTROLLER DESIGN MEETS ALL CEI FAIL-OPERATE/FAILSAFE REQUIREMENTS FOR THIS FAILURE MODE (1). REDUNDANT CONTROLLER CHANNEL FUNCTIONS ARE PHYSICALLY SEPARATED WITHIN THE CONTROLLER HOUSING (2). CIRCUITS ARE DESIGNED TO PREVENT BRIDGING (2), ALL PCB PARTS ARE REQUIRED TO HAVE CONFORMAL COATING, AND INTERNAL WIRING IS INSULATED TO PREVENT SHORT CIRCUITS FROM CONDUCTIVE CONTAMINATION (3). ALL ELECTRICAL COMPONENTS ARE CONTAINED WITHIN THE CASE STRUCTURE WHICH IS PRESSURIZED WITH A POSITIVE PRESSURE (INERT GAS BACKFILL) TO PREVENT CONTAMINATION (2). WHERE APPLICABLE, ELECTROMAGNETIC INTERFERENCE SHIELDING IS PROVIDED AND CIRCUIT INTERCONNECTS USE TWISTED PAIR WIRING (2). ALL CIRCUIT CARDS ARE KEYPED TO THEIR RESPECTIVE CONNECTION LOCATIONS TO PRECLUDE IMPROPER INSTALLATION (2). BAMP CLAMPS ARE UTILIZED TO PRECLUDE VIBRATION INDUCED CARD FAILURES (2). DESIGN OF CIRCUIT CARDS AND DETERMINATION OF COPPER PATH TRACE SPACING, WEIGHT, AND WIDTH IS CONTROLLED BY SPECIFICATION (2). EACH UNIT (PRODUCTION AND RECYCLE) IS REQUIRED TO PASS A FUNCTIONAL ACCEPTANCE TEST UNDER ENVIRONMENTAL CONDITIONS BEYOND THOSE SEEN DURING NORMAL FIELD OPERATION WITHOUT DEGRADATION OF HARDWARE LIFE EXPECTANCY (2). A WORST CASE CIRCUIT ANALYSIS WAS PERFORMED TO VERIFY NOMINAL OPERATION AT SPECIFICATION LIMITS (4). AN ANALYSIS WAS PERFORMED BY HONEYWELL TO ASSURE NO SINGLE POINT COMPONENT FAILURES ARE INHERENT TO THE CONTROLLER DESIGN (5).

(1) CP320R0003B
(2) DSHG8977A1
(3) 85M03928
(4) ES24472-01
(5) HONEYWELL BLOCK II
FMEA VOL I

{CIL ITEM: F200-80-02}

DESIGN

DOCUMENT REF.

DESIGN QUALIFICATION TESTING OF THE CONTROLLER ASSEMBLY HAS BEEN PERFORMED INCLUDING: FAULT INSERTION TESTING (1), ASSEMBLY THERMAL CYCLING (2), CASE AND ASSEMBLY VIBRATION TESTING (3), ELECTROMAGNETIC INTERFERENCE AND SUSCEPTIBILITY TESTING (4), ACOUSTICAL NOISE TESTING (5), CASE ULTIMATE PRESSURE TESTING (6), AND ASSEMBLY BREAK OPEN INSPECTION (7).

- (1) TR34079282
- TR34080202
- TR34088258
- TR34088259
- (2) TR34080203
- TR34080207
- (3) TR34080204
- TR34080205
- TR34080206
- TR34087499
- (4) TR34080209
- (5) TR34080210
- (6) TR34085021
- (7) TR34085022

{CIL ITEM: F200-80-02}

INSPECTION AND TEST

POSSIBLE CAUSES	SIGNIFICANT CHARACTERISTICS	INSPECTION(S)/TEST(S)	DOCUMENT REF.
ALL CAUSES:	RE1493 - CONTROLLER		RE1493
	ASSEMBLY INTEGRITY	CLEANLINESS REQUIREMENTS ARE VERIFIED PER SPECIFICATION DURING MANUFACTURING OF THE CONTROLLER ASSEMBLY.	RC1493
		ENVIRONMENT CONTROLS (TEMPERATURE, HUMIDITY) ARE ENFORCED DURING ASSEMBLY AND TESTING PER SPECIFICATION REQUIREMENTS.	DSHG8977A1
		TO PREVENT COMPONENT DAMAGE, STATIC ELECTRICAL DISCHARGE POTENTIAL IS CONTROLLED DURING MANUFACTURING PER SPECIFICATION REQUIREMENTS.	DSHG8977A1
	MATERIAL INTEGRITY	MATERIAL INTEGRITY IS VERIFIED PER SPECIFICATION REQUIREMENTS.	RC1493

CJL ITEM: F200-BD-02		INSPECTION AND TEST	
POSSIBLE CAUSES	SIGNIFICANT CHARACTERISTICS	INSPECTION(S)/TEST(S)	DOCUMENT REF.
	INTEGRITY OF ELECTRONICS	<p>PROTECTIVE FINISHES AND MATERIAL SELECTION TO PREVENT DETRIMENTAL EFFECTS FROM ENVIRONMENTAL EXPOSURE, STRESS CORROSION, AND ELECTROLYTIC CORROSION ARE VERIFIED PER SPECIFICATION REQUIREMENTS.</p> <p>FLAMMABILITY REQUIREMENTS ARE VERIFIED PER SPECIFICATION REQUIREMENTS.</p> <p>THE FOLLOWING PROCESSES ARE VERIFIED PER SPECIFICATION DURING MANUFACTURING OF THE CARD ASSEMBLIES:</p> <ul style="list-style-type: none"> - CONSTRUCTION OF PRINTED CIRCUIT BOARDS. - INSTALLATION OF TERMINALS. - PLASTICS AND ELASTOMERS FOR ELECTRONIC ENCAPSULATION. - SOLDERED ELECTRICAL CONNECTIONS. - POST-SOLDERING INSPECTION FREE OF SPLATTER AND CONTAMINATION. - ELECTRICAL BONDING. - COMPONENT LEAD AND INTERCONNECTION MATERIAL SELECTION. - FREE OF CONTAMINATION AFTER CONFORMAL COATING. 	<p>RC1493 MSFC-SPEC-250</p> <p>RC1493</p> <p>RL10005 RL10007 RL10008 RL10009 RL10009 RC1493 DSM03928 RC1493</p>
	WELD INTEGRITY	<p>ALL WELDS ARE VERIFIED TO DRAWING AND SPECIFICATION REQUIREMENTS.</p>	<p>RL10011</p>
	PRE-CLOSEOUT TESTING AND INSPECTION	<p>THE FOLLOWING TESTS ARE PERFORMED AT THE CARD/COMPONENT LEVEL DURING MANUFACTURING:</p> <ul style="list-style-type: none"> - PARTIAL IMPACT NOISE DETECTION (PIND) TEST ON HYBRID MICROCIRCUITS AND CAVITY TYPE DEVICES. - ULTRASONIC SCAN TEST FOR DELAMINATION CERAMIC ON CAPACITORS (CKR05 AND CKR06). - BURN-IN PERIOD FOR ELECTRICAL PARTS. - INSULATION RESISTANCE AND CONTINUITY TEST. - DIELECTRIC WITHSTANDING VOLTAGE. - FUNCTIONAL TEST. - X-RAY OF CONTROLLER INTERNAL CABLES AND WIRES. 	<p>DSHG8977A1 DSHG8977A1 DSM03928 DSHG8977A1 DSHG8977A1 DSHG8977A1 DSHG8977A1</p>

F-122

CIL ITEM: F200-BD-02		INSPECTION AND TEST	
POSSIBLE CAUSES	SIGNIFICANT CHARACTERISTICS	INSPECTION(S)/TEST(S)	DOCUMENT REF.
		<p>THE FOLLOWING INSPECTIONS ARE PERFORMED ON THE COMPLETED ASSEMBLY PRIOR TO FINAL CLOSURE:</p> <ul style="list-style-type: none"> - INTERNAL AND EXTERNAL CLEANLINESS. - CARD DIMENSIONS ARE VERIFIED AT CARD ASSEMBLY. - CHASSIS CAVITY INSPECTION FOR CONTAMINATION. - ELECTRICAL INTERFACE CONNECTORS. - CARD INSTALLATION AND CONFIGURATION AUDIT. - CONFORMAL COATING OF EEE PARTS. 	<p>RC1493 DSHG8977A1 RC1493 RC1493 DSHG8977A1 BSM03928</p>
	ACCEPTANCE TESTS	<p>THE FOLLOWING TESTS ARE PERFORMED BY HONEYWELL DURING ACCEPTANCE TESTING:</p> <ul style="list-style-type: none"> - HERMETIC SEAL AND PRESSURIZATION PORT LEAK TEST. - FUNCTIONAL TEST INCLUDING: <ul style="list-style-type: none"> - OUTPUT INTERFACE, - CHECKOUT, - OPERATION, - CONTROLLER CHECKOUT. - HIGH TEMPERATURE OPERATION. - LOW TEMPERATURE OPERATION. - VIBRATION TESTING. - FINAL FUNCTIONAL TEST. 	<p>RC1493 RC1493 RC1493 RC1493 RC1493 RC1493 RC1493 RC1493 RC1493</p>
	HOT FIRE ACCEPTANCE TESTING (GREEN BUR)	<p>CONTROLLER OPERATION IS VERIFIED THROUGH ENGINE HOT FIRE ACCEPTANCE TESTING.</p>	<p>RLO0461</p>
	HERMETIC SEAL INTEGRITY	<p>INTERNAL PRESSURE IS MONITORED DURING CONTROLLER OPERATION.</p>	<p>OMRSD V41AND.040</p>
	FLIGHT FLOW TESTING	<p>THE FOLLOWING TESTS ARE PERFORMED DURING FLIGHT FLOW VEHICLE PROCESSING AND AFTER ANY MAINTENANCE OR REPLACEMENT:</p> <ul style="list-style-type: none"> - CONTROLLER CHECKOUT. - IGNITER CHECKOUT. - FLIGHT READINESS TEST. - SELF-TEST. 	<p>OMRSD V41AR0.035 OMRSD V41ARD.010 OMRSD V41AS0.030-A CP406R0008</p>

F-123

[C.I.L. ITEM: F200-BD-02]		INSPECTION AND TEST	
POSSIBLE CAUSES	SIGNIFICANT CHARACTERISTICS	INSPECTION(S)/TEST(S)	DOCUMENT REF.
	PRE-FLIGHT CHECKOUT	THE FOLLOWING TESTS ARE PERFORMED DURING LAUNCH COUNTDOWN (LAST TEST): - PRE-CRYO LOADING CHECKOUT INCLUDING CONTROLLER, IGNITERS, AND SENSORS CHECKOUT. - SELF-TEST.	OMRSD SOOFAO.213 CP406R0008
FAILURE HISTORY: COMPREHENSIVE FAILURE HISTORY DATA IS MAINTAINED IN THE PROBLEM REPORTING DATABASE (PRMS/PRCA). REFERENCE: NASA LETTER SA21/88/308 AND ROCKETDYNE LETTER 88RC09761.			

OPERATIONAL USE: NOT APPLICABLE.