

FMEA NO. <u>W 5.12</u> CRITICALITY <u>2/2</u>	SHUTTLE CCTV CRITICAL ITEMS LIST	UNIT <u>Cable</u> DWG NO. <u>2293288-502, 503</u> ISSUED <u>10-14-86</u> SHEET <u>1</u> OF <u>5</u>
--	-------------------------------------	--

FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
Loss of +28V power RET Open	1) No PTU control 2) No video <u>Worst Case:</u> Loss of mission critical video.	<p><u>DESIGN FEATURES</u></p> <p>The WS Bulkhead cable is a 60-inch long assembly, 17-wire assembly originating at the cargo bay and bulkhead. The cable provides power and commands to cargo bay camera slack and returns video to the bulkhead position. The video and sync wires are shielded #24 Twinx twisted-pair wires.</p> <p>The cable design is taken from the successfully flown Apollo program. The design is a cable-connector assembly in which the wire terminations are protected from excessive flexure at the joint between the wire and the connector terminal. The load concentration is moved away from the conductor connection and distributed axially along the length of the conductors encapsulated in a potted-taper profile. This technique also protects the assembly from dirt and entrapped moisture which could cause problems in space.</p> <p>The cable and its components meet the applicable requirements of NASA, Military and RCA specifications. These requirements include:</p> <ul style="list-style-type: none"> • General/Mechanical/Electrical Features • Design and Construction • Materials • Terminal Solderability • Environmental • Qualification • Marking and Serialization • Traceability and Documentation

FMEA NO. <u>W 5.12</u> CRITICALITY <u>2/2</u>	SHUTTLE CCTV CRITICAL ITEMS LIST	<table border="1"> <tr> <td>INTL</td> <td>Cable</td> </tr> <tr> <td>DWG NO.</td> <td>2293208-502, 503</td> </tr> <tr> <td>ISSUED</td> <td>10-14-86</td> </tr> <tr> <td>SHEET</td> <td>2 OF 5</td> </tr> </table>	INTL	Cable	DWG NO.	2293208-502, 503	ISSUED	10-14-86	SHEET	2 OF 5
INTL	Cable									
DWG NO.	2293208-502, 503									
ISSUED	10-14-86									
SHEET	2 OF 5									
FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE								
Loss of +28V power RET Loss of video	1) No PTU control 2) No video Worst Case: Loss of mission critical video.	<p><u>QUALIFICATION TEST</u></p> <p>Qualified by 1.) similarity to previous successful space programs and 2.) by use during qualification tests of CCTV LRUs.</p> <p><u>ACCEPTANCE TEST</u></p> <p>The cable acceptance test consists of an ohmmeter check to assure that each wire connection is present and intact. Results are recorded on data sheets.</p> <p><u>OPERATIONAL TEST</u></p> <p>The following tests verify that CCTV components are operable and that the commands from the PHS (A7A1) panel switch, through the RCU, through the sync lines to the Camera/PTU, to the Camera/PTU command decoder are proper. The tests also verify the camera's ability to produce video, the VSU's ability to route video and the monitor's ability to display video. A similar test verifies the MDM command path.</p> <p><u>Pre-Launch on Orbiter Test/In-Flight Test</u></p> <ol style="list-style-type: none"> 1. Power CCTV System. 2. Select a monitor via the PHS panel, as destination and the camera under test as source. 3. Send "Camera Power On" command from PHS panel. 4. Select "External Sync" on monitor. 5. Observe video displayed on monitor. If video on monitor is synchronized (i.e., stable raster), then this indicates that the camera is receiving composite sync from the RCU and that the camera is producing synchronized video. 6. Send Pan, Tilt, Focus, Zoom, ALC, and Gamma commands and visually (either via the monitor or direct observation) verify proper operation. 7. Select Downlink as destination and camera under test as source. 8. Observe video routed to downlink. 9. Send "Camera Power Off" command via PHS panel. 10. Repeat Steps 3 through 9 except issue commands via the MDM command path. This proves that the CCTV equipment is operational if video is satisfactory. 								

FMEA NO. <u>W 5.12</u> CRITICALITY <u>2/2</u>	SHUTTLE CCTV CRITICAL ITEMS LIST	UNIT <u>Cable</u> DWG NO. <u>2293288-502, 503</u> ISSUED <u>10-18-86</u> SHEET <u>3</u> OF <u>5</u>
FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
Loss of +28V power RET open	1) No PTU control 2) No video <u>Worst Case:</u> Loss of mission critical video.	<p><u>QA/INSPECTION</u></p> <p><u>Procurement Control</u> - Wire, connectors, solder, etc. are procured from approved vendors and suppliers which meet the requirements set forth in the CCTV contract and Quality Plan Work Statement (NS-2593176).</p> <p><u>Incoming Inspection & Storage</u> - Incoming Quality inspections are made on all received materials and parts. Results are recorded by lot and retained in file by drawing and control numbers for future reference and traceability. Accepted items are delivered to Material Controlled Stores and retained under specified conditions until cable fabrication is required. Non-conforming materials are held for Material Review Board (MRB) disposition. (PAI-307, PAT IQC-53).</p> <p><u>Assembly & Test</u> - Prior to the start of assembly, all items are verified to be correct by stock room personnel as the items are accumulated to form a kit. The items are verified again by the operator who assembles the kit by checking against the as-built-parts-list (ABPL).</p> <p>Specific instructions are given in assembly drawing notes and applicable documents called out in the Fabrication Procedure and Record (FPR-2293288). These are 2280800 - Process Standard crimping flight connector contacts, 2280801 - Process Standard in-line splicing of standard interconnecting wire using Raychem solder sleeves, 2280875 - Process Standard marking of parts or assemblies with epoxy colors, 2280876. Potting material and test procedure (TP-AT-2293288). Quality and DCAS inspections are performed at the completion of key operations.</p> <p><u>Preparation for Shipment</u> - When fabrication and test is complete, the cable assembly is packaged according to 2280746, Process Standard for Packaging and Handling Guidelines. All related documentation including assembly drawings, Parts List, ABPL, Test Data, etc. is gathered and held in a documentation folder assigned specifically to each cable assembly. This folder is retained for reference.</p>

FMEA NO. <u>W 5.12</u> CRITICALITY <u>2/2</u>	SHUTTLE CCTV CRITICAL ITEMS LIST	UNIT <u>Cable</u> DWG NO. <u>2291288-502, 503</u> ISSUED <u>10-14-86</u> SHEET <u>4</u> OF <u>5</u>
--	-------------------------------------	--

FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
------------------------	----------------------------	--------------------------

Loss of +28V power RET ipen	1) No PTH control 2) No video Worst Case: Loss of mission critical video.	<p><u>FAILURE HISTORY</u></p> <p>There have been no reported failures during RCA testing, pre-flight or flight.</p>
--------------------------------	---	---

FMEA NO. <u>W 5.12</u> CRITICALITY <u>2/2</u>		SHUTTLE CCTV CRITICAL ITEMS LIST	DWT <u>Cable</u> DWG NO. <u>2293289-502, 503</u> ISSUED <u>TD-14-86</u> SHEET <u>5</u> OF <u>5</u>
FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE	
Loss of +28V power RET Open	1) No PTU control 2) No video <u>Worst Case:</u> Loss of mission critical video.	<u>OPERATIONAL EFFECTS</u> Loss of video. Possible loss of major mission objectives due to loss of RMS cameras or other required cameras. <u>CREW ACTIONS</u> If possible, continue RMS operations using alternate visual cues. <u>CREW TRAINING</u> Crew should be trained to use possible alternates to CCTV. <u>MISSION CONSTRAINT</u> Where possible procedures should be designed so they can be accomplished without CCTV.	