

REVISED 5-7-87

FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
<p>Loss of video out (positive) Short to GND</p>	<p>1/2 amplitude video out. <u>Worst Case:</u> Loss of mission critical video.</p>	<p><u>DESIGN FEATURES</u></p> <p>The W8 wrist/TVC cable is a 19-inch long assembly, 14-wire assembly originating at the RMS wrist with a 26-pin connector (Pl1, PV6616S26PND16) and terminating at a TVC with a 37-pin connector (Pl1, KJ66E14N35SN16). The video and sync wires are shielded #24 Twinax twisted-pair wires. The W8 cable provides power and commands from the RVS to the wrist or elbow camera stack.</p> <p>The cable design is taken from the successfully flown Apollo program. The design is a cable-connector assembly in which the wire terminations are protected from excessive flexure at the joint between the wire and the connector terminal. The load concentration is moved away from the conductor connection and distributed axially along the length of the conductors encapsulated in a potted-taper profile. This technique also protects the assembly from dirt and entrapped moisture which could cause problems in space.</p> <p>The cable and its components meet the applicable requirements of NASA, Military and RCA specifications. These requirements include:</p> <ul style="list-style-type: none"> <li>• General/Mechanical/Electrical Features</li> <li>• Design and Construction</li> <li>• Materials</li> <li>• Terminal Solderability</li> <li>• Environmental</li> <li>• Qualification</li> <li>• Marking and Serialization</li> <li>• Traceability and Documentation</li> </ul>

UNIT Cable  
 DWG NO. 2293289-501  
 ISSUED 10-14-86  
 SHEET 1 OF 5

SHUTTLE CCTV  
 CRITICAL ITEMS LIST

FMEA NO. W 8.1  
 CRITICALITY 2/2

FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
FMEA NO. <u>M 8.1</u> CRITICALITY <u>2/2</u>		SHUTTLE CCTV CRITICAL ITEMS LIST ONLY Cable DWG NO. 2293289-501 ISSUED 10-14-86 SHEET 2 OF 5
s of video out (positive) n/Short to GND	1/2 amplitude video out. <u>Worst Case:</u> Loss of mission critical video.	<u>QUALIFICATION TEST</u> Qualified by 1.) similarity to previous successful space programs and 2.) by use during qualification tests of CCTV LRHs. <u>ACCEPTANCE TEST</u> The cable acceptance test consists of an ohmmeter check to assure that each wire connection is present and intact. Results are recorded on data sheets. <u>OPERATIONAL TEST</u> The following tests verify that CCTV components are operable and that the commands from the PHS (AZA) panel switch, through the RCU, through the sync lines to the Camera/PTU, to the Camera/PTU command decoder are proper. The tests also verify the camera's ability to produce video, the VSU's ability to route video and the monitor's ability to display video. A similar test verifies the NDM command path. <u>Pre-Launch on Orbiter Test/In-Flight Test</u> <ol style="list-style-type: none"> <li>1. Power CCTV System.</li> <li>2. Select a monitor via the PHS panel, as destination and the camera under test as source.</li> <li>3. Send "Camera Power On" command from PHS panel.</li> <li>4. Select "External Sync" on monitor.</li> <li>5. Observe video displayed on monitor. If video on monitor is synchronized (i.e., stable raster), then this indicates that the camera is receiving composite sync from the RCU and that the camera is producing synchronized video.</li> <li>6. Send Pan, Tilt, Focus, Zoom, ALC, and Gamma commands and visually (either via the monitor or direct observation) verify proper operation.</li> <li>7. Select Downlink as destination and camera under test as source.</li> <li>8. Observe video routed to downlink.</li> <li>9. Send "Camera Power Off" command via PHS panel.</li> <li>10. Repeat Steps 3 through 9 except issue commands via the NDM command path. This proves that the CCTV equipment is operational if video is satisfactory.</li> </ol>

REVISED 5-7-87

REQ NO. <u>W.B.1</u>	SHUTTLE CCTV CRITICAL ITEMS LIST	UNIT <u>Cable</u> DWG NO. <u>2293289-501</u> ISSUED <u>10-14-86</u> SHEET <u>3</u> OF <u>5</u>
CRITICALITY <u>2/2</u>		

FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	RATIONALE FOR ACCEPTANCE
of video out (positive) /Short to GND	1/2 amplitude video out. <u>Worst Case:</u> Loss of mission critical video.	<p><u>QA/INSPECTION</u></p> <p><u>Procurement Control</u> - Wire, connectors, solder, etc. are procured from approved vendors and suppliers which meet the requirements set forth in the CCTV contract and Quality Plan Work Statement (WS-2593176).</p> <p><u>Incoming Inspection &amp; Storage</u> - Incoming Quality inspections are made on all received materials and parts. Results are recorded by lot and retained in file by drawing and control numbers for future reference and traceability. Accepted items are delivered to Material Controlled Stores and retained under specified conditions until cable fabrication is required. Non-conforming materials are held for Material Review Board (MRB) disposition. (PAI-307, PAI IQC-53).</p> <p><u>Assembly &amp; Test</u> - Prior to the start of assembly, all items are verified to be correct by stock room personnel as the items are accumulated to form a kit. The items are verified again by the operator who assembles the kit by checking against the as-built-parts-list (ABPL).</p> <p>Specific instructions are given in assembly drawing notes and applicable documents. These are 2280800 - Process Standard crimping flight connector contacts, 2280801 - Process Standard in-line splicing of standard interconnecting wire using Raychem solder sleeves, 2280876 - Process Standard marking of parts or assemblies with epoxy colors, 2280876. Potting material and test procedure (TP-AI-2293289). Quality and BCAS inspections are performed at the completion of key operations.</p> <p><u>Preparation for Shipment</u> - When fabrication and test is complete, the cable assembly is packaged according to 2280746, Process Standard for Packaging and Handling Guidelines. All related documentation including assembly drawings, Parts list, ABPL, Test Data, etc. is gathered and held in a documentation folder assigned specifically to each cable assembly. This folder is retained for reference.</p>

REVISED 5-7-87

FMEA NO. W 8.1  
 CRITICALITY 2/2

SHUTTLE CCTV  
 CRITICAL ITEMS LIST

UNIT Cable  
 DWG NO. 2293289-501  
 ISSUED 10-14-86  
 SHEET 4 OF 5

FAILURE MODE AND CAUSE	FAILURE EFFECT OR END ITEM	RATIONALE FOR ACCEPTANCE
Loss of video out (positive) open/Short to GND	1/2 amplitude video out. <u>Worst Case:</u> Loss of mission critical video.	<u>FAILURE HISTORY</u> There have been no reported failures during RCA testing, pre-flight or flight.

REVISED 5-7-87

FMEA NO. 4 B.1

CRITICALITY 2/2

SHUTTLE CCTV  
CRITICAL ITEMS LIST

UNIT Cable  
 DWG NO. 2293289-501  
 ISSUED 10-14-86  
 SHEET 5 OF 5

FAILURE MODE AND CAUSE	FAILURE EFFECT OR END ITEM	RATIONALE FOR ACCEPTANCE
Loss of video out (positive) Open/Short to GND	1/2 amplitude video out. <u>Worst Case:</u> Loss of mission critical video.	<u>OPERATIONAL EFFECTS</u> Loss of video. Possible loss of major mission objectives due to loss of RMS cameras or other required cameras. <u>CREW ACTIONS</u> If possible, continue RMS operations using alternate visual cues. <u>CREW TRAINING</u> Crew should be trained to use possible alternates to CCTV. <u>MISSION CONSTRAINT</u> Where possible procedures should be designed so they can be accomplished without CCTV.